

DS-L

DMX512-SPI Decoder and RF Controller

DMX512

Features

- DMX512 to SPI decoder and RF controller with digital display.
- Compatible with 47 kinds of digital IC RGB or RGBW LED strip, IC type and R/G/B order can be set.
Compatible ICs: TM1803, TM1804, TM1809, TM1812, UCS1903, UCS1909, UCS1912, SK6813, UCS2903, UCS2909, UCS2912, VWS2811, VWS2812, VWS2813, VWS2815, TM1829, TLS3001, TLS3002, GW6205, MBI6120, TM1814B(RGBW), SK6812(RGBW), SM16714(RGBW), SM16703P, SM16714D, VWS2813(RGBW), VWS2814(RGBW), UCS8904B(RGBW), LPD6803, LPD1101, D705, UCS6909, UCS6912, LPD8803, LPD8806, VWS2801, VWS2803, P9813, SK9822, TM1914A, GS8206, GS8208, UCS2904, SM16804, SM16825, UCS5603, UCS2603.
- DMX decode mode, stand-alone mode and RF mode selectable.
- Standard DMX512 compliant interface, set DMX decode start address by buttons.
- Under stand-alone mode, change mode, speed or brightness by buttons.
- Under RF mode, match with RF 2.4G RGB/RGBW remote control.
- 32 kinds dynamic mode, include horse-race, chase, flow, trail or gradual change style.




FC CE RoHS

Technical Parameters


Input and Output		Environment	Safety and EMC	
Input voltage	5-24VDC	Operation temperature	Ta: -30°C ~ +55°C	EMC standard
Input current	10A	Case temperature(Max.)	Tc: +65°C	EN IEC 55015/ EN IEC 61547
Power consumption	1W	IP rating	IP20	Safety standard
Input signal	DMX512 + RF 2.4GHz	Package	Size	EN 61347-1/-2 EN 62493
Output signal	SPI(TTL) x 2			Certification
Dynamic mode	32	Gross weight	0.122kg	CE RoHS FCC
Control dots	170 pixels (RGB 510 CH) Max 900pixels	Warranty		Warranty
				5 years

Mechanical Structures and Installations




Wiring Diagram

- LED strip load current $\leq 10A$



- LED strip load current $> 10A$



Note:

- If the SPI LED pixel strip is single-wire control, the DATA and CLK output is same, we can connect up to 4 LED strips.
- If the SPI LED pixel strip is two-wire control, we can connect up to 2 LED strips.
- When the strip light load exceeds 10A, the controller and strip light require separate power supplies.
If the strip light uses single-wire control, only the DATA and GND signal wires connect the controller to the strip light.
If the LED strip uses a dual-wire control method, only the DATA, CLK, and GND wires connect the controller to the LED strip.

IC type, RGB/RGBW order and pixel length length setting

- Diagram illustrating the output of the 7-segment display for different configurations:

 - IC type: C 12
 - RGB order: 0-1
 - W&RGB order (RGBW only): 0c4
 - pixel length: 170
 - disable automatic blank screen: bof

No.	IC type	Output signal
C11	TM1803	DATA
C12	TM1809,TM1804,TM1812,UCS1903,UCS1909,UCS1912,SK6813,UCS2903,UCS2909,UCS2912,WS2811,WS2812,WS2813,WS2815,SM16703P	DATA
C13	TM1829	DATA
C14	TLS3001,TLS3002	DATA
C15	GW6205	DATA
C16	MBI6120	DATA
C17	TM1814B(RGBVV)	DATA
C18	SK6812(RGBVV),WS2813(RGBVV),WS2814(RGBVV)	DATA
C19	UCS8904B(RGBVV)	DATA
C21	LPD6803,LPD1101,D705,UCS6909,UCS6912	DATA,CLK
C22	LPD8803,LPD8806	DATA,CLK
C23	WS2801,WS2803	DATA,CLK
C24	P9813	DATA,CLK
C25	SK9822	DATA,CLK
C31	TM1914A	DATA
C32	GS8206,GS8208	DATA
C33	UCS2904	DATA
C34	SM16804	DATA
C35	SM16825	DATA
C36	SM16714(RGBVV)	DATA
C37	UCS5603	DATA
C38	UCS2603	DATA
C39	SM16714D	DATA

- DMX decode mode

DMX decode mode 3: the DMX data change light directly (One data copy triple, control one pixel, for SPI type white light strip).



DMX decode mode

Long press M key for 2s, and then return to DMX address interface.

- Short press M key, when display 001-512, enter DMX decode mode.
- Press ◀ or ▶ key to change DMX decode start address(001-512), long press for fast adjustment.
- Long press M key for 2s, prepare for setup decode number and multiple of pixels.

Short press M key to switch two item.

Press ◀ or ▶ key to setup value of each item.

Decode number(display "dno") : DMX decode channel number, range is 003-600(for RGB).

Multiple of pixels(display "Pno") : Each 3 DMX channel control length (for RGB), range is 001- pixel length.

Long press M key for 2s, or timeout 10s, quit setting.

- If there is a DMX signal input, will enter DMX decode mode automatically.

DMX data from DMX512 console:

DMX CH	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18
DMX Data	255	0	0	0	255	0	0	0	255	255	255	0	0	255	255	255	0	255

$\oplus$ V+ $\rightarrow$

① V+ ② V- ③ DA ④ VA

- Short press M key, when display 001-512, Press ◀ or ▶ key to change DMX decode start address(001-512), long press for fast adjustment.
For example, when the DMX start address is set to 001. The address 1 of DMX console is for dynamic light type setting (32 modes), address 2 is for brightness setting (10 levels), address 3 is for speed setting (10 levels).
Long press M key for 2s, or timeout 10s, quit setting.
- Address 1 of DMX console: dynamic light mode

1: 0-8	2: 9-16	3: 17-24	4: 25-32	5: 33-40	6: 41-48	7: 49-56	8: 57-64
9: 65-72	10: 73-80	11: 81-88	12: 89-96	13: 97-104	14: 105-112	15: 113-120	16: 121-128
17: 129-136	18: 137-144	19: 145-152	20: 153-160	21: 161-168	22: 169-176	23: 177-184	24: 185-192
25: 193-200	26: 201-208	27: 209-216	28: 217-224	29: 225-232	30: 233-240	31: 241-248	32: 249-255

- Address 2 of DMX console: Brightness (When address 2 data <5, turn off the light)
1: 5-25 (10%) 2: 26-50 (20%) 3: 51-75 (30%) 4: 76-100 (40%) 5: 101-125 (50%)
6: 126-150 (60%) 7: 151-175 (70%) 8: 176-200 (80%) 9: 201-225 (90%) 10: 226-255 (100%)
- Address 3 of DMX console : Speed
1: 0-25 (10%) 2: 26-50 (20%) 3: 51-75 (30%) 4: 76-100 (40%) 5: 101-125 (50%)
6: 126-150 (60%) 7: 151-175 (70%) 8: 176-200 (80%) 9: 201-225 (90%) 10: 226-255 (100%)

DMX decode mode 3:

- Short press M key, when display 001-512, enter DMX decode mode.
- Press ◀ or ▶ key to change DMX decode start address (001-512), long press for fast adjustment.
- Long press M key for 2s, prepare for setup decode number and multiple of pixels.
Short press M key to switch two item.
Press ◀ or ▶ key to setup value of each item.
Decode number (display “dno”) : DMX decode channel number, range is 001-512.
Multiple of pixels (display “Pno”) : Each one DMX channel control length, range is 001-pixel length.
Long press M key for 2s, or timeout 10s, quit setting.
- If there is a DMX signal input, will enter DMX decode mode automatically.

The DMX-SPI decoder connect with white strip, one DMX data control three LED beads:

For example, DMX data from DMX512 console:

DMX CH	1	2	3	4	5	6
DMX Data	255	192	128	64	0	255

DMX-SPI decoder output (start address: 001, decode channel number: 6, each one channel control length: 1):

Output data	255	255	255	192	192	192	128	128	128	64	64	64	0	0	0	255	255	255
-------------	-----	-----	-----	-----	-----	-----	-----	-----	-----	----	----	----	---	---	---	-----	-----	-----

DMX-SPI decoder output (start address: 001, decode channel number: 6, each one channel control length: 2):

Output data	255	255	255	255	255	255	192	192	192	192	192	128	128	128	128	128	128
	64	64	64	64	64	64	0	0	0	0	0	0	0	0	255	255	255

Stand-alone mode

- Short press M key, when display P01-P32, enter stand-alone mode.
- Press ◀ or ▶ key to change dynamic mode number (P01-P32).
- Each mode can adjust speed and brightness.
Long press M key for 2s, prepare for setup mode speed and brightness.
Short press M key to switch two item.
Press ◀ or ▶ key to setup value of each item.
Mode speed: 1-10 level speed (S-1, S-9, S-F).
Mode brightness: 1-10 level brightness (b-1, b-9, b-F).
Long press M key for 2s, or timeout 10s, quit setting.
- Enter stand-alone mode only when DMX signal is disconnected or lost.



Dynamic mode list

No.	Name	No.	Name	No.	Name
P01	Red horse race white ground	P12	Blue White chase	P23	Purple float
P02	Green horse race white ground	P13	Green Cyan chase	P24	RGBW float
P03	Blue horse race white ground	P14	RGB chase	P25	Red Yellow float
P04	Yellow horse race blue ground	P15	7 color chase	P26	Green Cyan float
P05	Cyan horse race blue ground	P16	Blue meteor	P27	Blue Purple float
P06	Purple horse race blue ground	P17	Purple meteor	P28	Blue White float
P07	7 color multi horse race	P18	White meteor	P29	6 color float
P08	7 color horse race close + open	P19	7 color meteor	P30	6 color smooth sectionally
P09	7 color multi horse race close + open	P20	Red float	P31	7 color jump sectionally
P10	7 color scan close + open	P21	Green float	P32	7 color strobe sectionally
P11	7 color multi-scan close + open	P22	Blue float		

RF mode

Match: Long press M and ▶ key for 2s, display “RLS”, within 5s, press on/off key of the RGB remote, display “RLO”, match is successful, then use the RF remote to change mode number, adjust speed or brightness.
Delete: Long press M and ▶ key for 5s, until display “RLE”, delete all matched RF remote.
Note: DMX signal control and RF remote control can't work at the same time. when matching RF remote control, please disconnect the DMX signal input first.

Restore factory default parameter

- Long press ◀ and ▶ key, restore factory default parameter, display “RES”.
- Factory default parameter: DMX decode mode 1, DMX decode start address is 1, decode number is 510, multiple of pixels 1, dynamic mode number is 1, chip type is TM1809, RGB order, pixel length is 170, disable automatic blank screen, without matched RF remote.

Statement

FCC Statement:
This device complies with Part 15 of the FCC Rules. operation is subject to the following two conditions:
(1) this device may not cause harmful interference, and
(2) this device must accept any interference received, including interference that may cause undesired operation.
IC Statement: This Class B digital apparatus complies with Canadian ICES-003.
(Cet appareil numérique de la Classe B conforme à la norme NMB-003 du Canada).