


SS-C3

RF 3 Channels Smart Switch

Features

- RF high-voltage 3 channel AC switch, relay output, per channel can output current 3A, maximum total output power is 2160W, with zero-crossing detection function.
- Suitable for turning on/off single color LED lights, traditional incandescent and halogen lights, no dimming function.
- With an LED indicator.
- Match with RF 2.4G remote control.




CE RoHS

Technical Parameters


Input and Output		Environment		Safety and EMC	
Input voltage	100-240VAC	Operation temperature	Ta: -20°C ~ +55°C	Safety standard	EN 61347-1/-2
Output voltage	3x(100-240)VAC	Case temperature (Max.)	Tc: +77°C		EN IEC 55015/ EN IEC 61547
Output current	3x3A (Resistive/Capacitive/ Inductive loads)	IP rating	IP20	EMC standard	EN IEC 61000-3-2/ EN IEC 61000-3-3 ETSI EN 301 489-1/-3
Output power	3x(300-720)W	Package		Radio equipment	ETSI EN 300 440
Relay surge current	205A	Size	L1 10x W57x H35mm	Certification	CE RoHS
Input signal	RF 2.4GHz	Gross weight	0.08kg	Warranty	
Control distance	30m(Barrier-free space)			Warranty	5 years

Mechanical Structures and Installations



AC Switch

Wiring Diagram



Note:
Long press the Match key for 10s to restore factory default settings, clear all pairings, and keep all channel relays in the "on" state.

Match with RF Remote Controller

There are two ways to match/delete:

Use Match key

Match:
Short press match key, the LED indicator flash slowly. Immediately press on/off key on the three zone remote. The LED indicator fast flash means match is successful.

Delete:

Press and hold match key for 5s to delete all match, the LED indicator fast flash 6 times means all matched remotes were deleted.

Use Power Restart

Match:
Switch off the power, then switch on power, repeat again. Immediately short press on/off key 3 times on the three zone remote. The light indicator blinks 3 times means match is successful.

Delete:

Switch off the power, then switch on power, repeat again. Immediately short press on/off key 5 times on the three zone remote. The light indicator blinks 5 times means all matched remotes were deleted.

TC Point Location

The Tc point is located at the top of the Smart Switch

